



Flaming River Industries, Inc.  
 800 Poertner Drive Berea, OH 44017  
 1-800-648-8022 | www.flamingriver.com

### The Little Switch Product Specifications Sheet

		
Description	<b>The Little Switch – With Mounting Bracket</b>	<b>The Little Switch – No Mounting Bracket</b>
Part No.	<a href="#">FR1002</a>	<a href="#">FR1002-1</a>
Warranty	3 Years	3 Years
Voltage	6V/12V/24V	6V/12V/24V
Max Continuous Current	100 Amps	100 Amps
Max Surge Current	500 Amps (10 seconds)	500 Amps (10 seconds)
Environmental Protection Rating	IP4X	IP4X
Operating Temperature Range	-40°C to +50°C -40°F to +122°F	-40°C to +50°C -40°F to +122°F
Contact Terminals	Copper	Copper
Contact Hardware	Zinc Plated Steel	Zinc Plated Steel
Stud Diameter	M8	M8
Available Stud Length	0.50"	0.50"
Max Tightening Torque	4.43 ft·lbs / 6 N·m	4.43 ft·lbs / 6 N·m
LED ON/OFF Indicator	No	No
Lock-Out Capability	Yes – Removable Key	Yes – Removable Key
Replacement Key Part No.	FR1002K	FR1002K
Mounting Bracket Included	Yes	No
Mounting Bracket Part No.	FR1004	FR1004
Protective Cover Included	Yes - Protective Rubber Boot	Yes - Protective Rubber Boot
Protective Cover Part No.	FR1002BT	FRE1002BT
Extension Handle/Lever	No	No
Extension Part No.	N/A	N/A
Additional Notes	Approved for IMSA, ARCA, and SCCA competition use	Approved for IMSA, ARCA, and SCCA competition use

**WARNING:** Flaming River Industries, Inc. make no recommendation as to mounting location or product suitability to your vehicle application. For each kit, contact your vehicle’s manufacturer to determine proper placement and suitability. When installed, a battery disconnect switch is a functioning and live part of the electrical current system and should be treated like battery terminals.