


Flaming River Ind. 800 Poertner Dr Berea, OH 44017 800-648-8022

Electro Wizard™ Battery Disconnect Switch



FR1051 Mounting Diagram Positive Disconnection, 12V

Positive Disconnection, 12V Grounded Solenoid (Power Supply Coil Negative)



FR1051 Technical Specifications

Positive Disconnection, 12V Grounded Solenoid (Power Supply Coil Negative)

CHARACTERISTICS	FR 1051
Nominal tension	Max 12V
Max. continuous current on main contacts	250 A (23°C / 73.4°F)
Max. short time current on main contacts	2500 A x 3 sec.
Recommended wire section	>75mm² / 0.116 sq in
Protection degree	IP 65
Tightening torque M10 nuts	20 Nm / 14.75ft lb
Tightening torque M5 nuts	1.6 Nm / 1.18 ft lb
Operating temperature range	-40°C/+85°C -40°F/+185°F
Contacts	Silver plated copper
Contact terminals	M10 tin-plated brass
Nuts for contacts	Brass
Peak current coil rated input	4.4 A
Max. retaining coil	3.2 A
Holding coil rated input	0.4 A

FITTING INSTRUCTIONS:	ELECTRICAL DIAGRAM
The battery isolator switch must be placed as close as possible to the batteries. To avoid corrosion to wires and terminals, mount in a protected location. It can be fixed to the frame according to the fitting diagram shown in the drawing, using M 8 TCEI (cylindrical head – encased hexagon) screws UNI 5931: 1984, and plain washers 8,4x1.7 UNI 6592:1969. The inversion of the power supply to the coil causes serious damage to the internal diode.	30A 30 30 85

FR1051

Positive Disconnection, 12V Grounded Solenoid (Power Supply Coil Negative)

The Flaming River FR1051 Disconnect Switch is designed to disconnect a vehicle electrical system using a toggle switch (Not Included). The disconnect switch should be located as close as possible to the battery. The toggle switch can be located in any convenient location for ease of operator use.


- 1. Positive battery cable is connected to terminal 30 (POS BATT.)
- 2. Vehicle load is connected to terminal 30A (POS.TEL.)
- 3. From terminal 85 (NEG.BOB.), connect a wire to one side of the toggle switch. (Any style of "maintained" switch is acceptable, 10 amp or greater).
- 4. Connect the other side of the toggle switch to chassis ground.

When the operator closes the toggle switch, the solenoid in the disconnect switch is activated. The switch will remain closed (on) as long as terminal 85 is grounded.

- Always use proper wiring techniques.
- Wire size should be determined using industry standards based upon load requirements and length of cable needed.
- Activation solenoid has a max draw of 4.4 amps, 0.4 amps continuous.
- Main terminals are rated for 250 amps continuous, 2500 amps peak.
- We always recommend the use of Battery Terminal Covers FR1003TM.

<u>FR1051 Wiring Diagram</u>


Positive Disconnection, 12V Grounded Solenoid (Power Supply Coil Negative)





FR1052 Mounting Diagram Positive Disconnection, 12V

Positive Disconnection, 12V Insulated Solenoid (Power Supply Coil From Battery)

FR1052-ASM, SWITCH 12V INSULATED SOLENOID This drawing is for reference only and is the property of Flaming River Industries







FR1052 Technical Specifications Positive Disconnection, 12V

CHARACTERISTICS	FR1052
Nominal tension	Max 12V
Max. continuous current on main contacts	250 A (23°C / 73.4°F)
Max. short time current on main contacts	2500 A x 3 sec.
Recommended wire section	>75mm² / 0.116 sq in
Protection degree	IP 65
Tightening torque M10 nuts	20 Nm / 14.75ft lb
Tightening torque M5 nuts	1.6 Nm / 1.18 ft lb
Operating temperature range	-40°C/+85°C -40°F/+185°F
Contacts	Silver plated copper
Contact terminals	M10 tin-plated brass
Nuts for contacts	Brass
Peak current coil rated input	4.4 A
Max. retaining coil	3.2 A
Holding coil rated input	0.4 A

FITTING INSTRUCTIONS:	ELECTRICAL DIAGRAM
The battery isolator switch must be placed as close as possible to the batteries. To avoid corrosion to wires and terminals, mount in a protected location. It can be fixed to the frame according to the fitting diagram shown in the drawing, using M 8 TCEI (cylindrical head – encased hexagon) screws UNI 5931: 1984, and plain washers 8,4x1.7 UNI 6592:1969. The inversion of the power supply to the coil causes serious damage to the internal diode.	30A - 31A 30 - 31

FR1052

Positive Disconnection, 12V Insulated Solenoid (Power Supply Coil From Battery)

The versatility of Flaming River's FR1052 Disconnect Switch allows for multiple installation options based upon user need and vehicle application.

Options:

- A. Include positive or negative electrical disconnection
- B. Positive or negative switching.
- C. Continuous operator controlled remote "on", and Passive disconnect via vehicle ignition off.
- D. The addition of the FR1053 Time Delay Relay makes the switch suitable for vehicles requiring a Selective Catalytic Reduction cleaning cycle or other custom features.

The disconnect switch should be located as close as possible to the battery.

Common Installations:

Operator controlled ON-OFF (+/- disconnect and switching)

- 1. Positive or negative battery cable is connected to terminal 30-31.
- 2. Vehicle load (+/-) is connected to terminal 30A-31A
- 3. User determines +/- switching. Term. 85 switched for negative, Term. 86 switched for positive. Un-switched side: 85 chassis ground, 86 positive. (Any style of "maintained" switch is acceptable, 10 amp or greater)


FR1052

Positive Disconnection, 12V Insulated Solenoid (Power Supply Coil From Battery)


Passive Disconnect (Ignition OFF Battery Disconnection) This installation uses a momentary switch (Not Included) to energize the vehicles electrical system, then uses the ignition system to maintain the disconnect switch in the closed (on) position. When the ignition is turned off, the disconnect switch automatically opens (off) and the electrical system is disconnected.

- 1. Positive battery cable is connected to terminal 30-31
- 2. Vehicle load is connected to terminal 30A-31A
- 3. Terminal 85 (NEG.BOB.) is connected to chassis ground.
- 4. Terminal 86 (POS.BOB.) is connected to one side of momentary switch and is connected to an "ignition on" circuit (i.e. Switch "IGN/ RUN" terminal)
- 5. Other side of momentary switch is connected to constant positive. (Any style of momentary switch is acceptable, 10 amp or greater).
- · Always use proper wiring techniques.
- Wire size should be determined using industry standards based upon load requirements and length of cable needed.
- Activation solenoid has a max draw of 4.4 amps, 0.4 amps continuous.
- Main terminals are rated for 250 amps continuous, 2500 amps peak.
- We always recommend the use of Battery Terminal Covers FR1003TM.


FR1052 Wiring Diagram




FR1052 Wiring Diagram



<u>FR1052 Wiring Diagram</u>



FR1052 Wiring Diagram



WARRANTY

MENBER'S guarantees the product 24 months (from the time of sale) against fabrication defects in compliance with applicable laws and terms of liability. All damages caused by improper – handling, installation, use, service or lack of service will void warranty. It is also excluded malfunctions attributable to outside phenomena, MENBER'S will take over the possible replacement of the defective product at its discretion. In case of controversies or disputes related to the product and/or interpretation of the warranty conditions the competent FORM OF VERONA.

WARRANTY DISCLAIMER: Flaming River's Limited Warranty Flaming River warrants its products to be free from defects in material and workmanship for a period of one (1) year after the date of purchase, except that: All steering columns are warranted for a period of three (3) years from the date of purchase. The Big Switch (part number FR1005) is warranted for a period of three (3) years from the date of purchase, provided that it is not mounted with a steel bracket and provided further that it is adequately protected from environmental conditions. All electrical products other than the Big Switch are warranted for a period of ninety (90) days from the date of purchase. Flaming River's warranty liability is limited to the replacement of defective products. Flaming River is not liable for any labor costs associated with any warranty claim, or for any incidental or consequential damages. Improper installation, abuse, racing, and/ or modification of the products voids this warranty. No warranty of merchantability or fitness for a particular purpose is made by Flaming River with respect to any of its products.

WARNINGS AND RECOMMENDATIONS

It is the customer's responsibility to determine the suitability of a given Flaming River product for the customer's uses. Likewise, it is the customer's responsibility to install a Flaming River product. Contact the vehicle manufacturer whenever installing a switch to confirm the appropriateness of using such a switch and the recommended placement of the switch on the vehicle. Use qualified chassis specialists for the installation of all steering related components. Be aware that the installation of certain Flaming River products may adversely impact a manufacturer's warranty with respect to certain vehicles and other manufactured goods. Flaming River will repair or replace any product found to be defective in material or workmanship. Improper installation, abuse, racing and/or modification VOID WARRANTY. Flaming River is not responsible for any labor costs associated with any warranty.



Flaming River Industries 800 Poertner Dr., Berea, OH 44017 800-648-8022 • www.flamingriver.com